

Product Code: SFPW852PW

Description: 13A Lockable Switched Fused Connection Unit With Neon



### General Information

|  |  |   |
|--|--|---|
| Insert Dimensions (mm)                 | 82.5 (W) x 82.5 (H) x 2.5 (D)  |   |
| Plate Dimensions (mm)                  | 86 (W) x 86 (H) x 4 (D)  |   |
| Plate Fixing Centres - Horizontal (mm) | 60.3   |   |
| Style                                  | Screwless Complete   |   |
| Finish                                 | Polar White  |   |
| Insert Colour                          | Polar White  |   |
| Compatible Cover Plate                 | SCP452#  |   |
| Materials                              | Cover Plate: Polycarbonate<br>Rear Housing: Urea<br>Neon Lens: Polycarbonate<br>Terminal Screws: Steel & Yellow Passivated<br>Internal Busbars: Formed Pressed Brass | Insert: Polycarbonate<br>Fuse Drawer & Switch: Polycarbonate<br>Terminals: Brass<br>Contacts: Silver "on-lay" Copper / Brass<br>Earth Strap: Mild Steel |
| Anti Microbial Certified               | No   |   |
| Rated Voltage (V~) (Ue)                | 250  | Frequency (Hz) 50   |
| Resistive Load Rating (A)              | 13   |   |
| Fuse Fitted Rating & Type              | 13A (BS 1362)  |   |
| Termination Type                       | Screw  |   |
| Terminal Size (mm)                     | Ø5   | Terminal Torque Value (Nm) 2  |
| Terminal Capacity - Solid (mm²)        | 3 x 2.5 or 2 x 4   |   |
| Switched                               | Yes  |   |
| Double Pole Switch                     | Yes  |   |
| Twin Earth Terminals                   | Yes  |   |
| Neon Indicator                         | Yes  | Indicator Colour Red  |
| Product Marking                        | Fused  |   |
| Minimum Back Box Depth (mm)            | 35   |   |
| Ingress Protection                     | IP20   |   |
| Operational Temperature (°C)           | -5 to +40  |   |
| Warranty (Years)                       | 10   |   |
| Standards                              | BS 1363-4<br>BS 1362   |   |

### Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.  
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.