



13A USB Power Socket Outlets



Eliminate the need for bulky chargers and free up your plug sockets with a 2 gang switch with integrated USB. The convenient USB port is centrally located to avoid cable interference from anything that maybe be plugged into the sockets.

Suitable for most tablets, smart phones, cameras and other USB devices, all of which can still be used whilst charging. Our single USB output guarantees optimum charge rate regardless of the device charging.

Scolmore International Ltd, 1 Scolmore Park, Landsberg, Lichfield Road Ind. Estate, Tamworth, Staffordshire, B79 7XB

Telephone: 01827 63454

E-mail: sales@scolmore.com, technical@scolmore.com

Facsimile: 01827 63362

Website: www.scolmore.com

13A USB Power Socket Outlets

Product Range

13A USB Power Socket Outlets

CMA771AG	13A 1 Gang Switched Socket with Single USB Charging Outlet
CMA770AG	13A 2 Gang Switched Socket with Single USB Charging Outlet



CMA771AG




CMA770AG


13A USB Power Socket Outlets

Product Dimensional Drawings (mm)


CMA771AG



CMA770AG



Product Wiring Diagram



13A USB Power Socket Outlets**Technical Specification****13A USB Power Socket Outlets**

Material Composition	Front Plate, Rocker Switch & Rear Housing: Urea
	Terminals: Brass, Terminal Screws: Steel & Yellow Passivated
	Earth Strap: Mild Steel, Silver “on-lay” Copper / Brass Contacts
Voltage	240V~ 50Hz
Current Rating	13A
Terminal Size	5mm ø
Torque Value	2.5Nm
Cable Size	4 x 2.5mm ²
Back Box Depth	35mm - 47mm (1 Gang), 25mm - 47mm (2 Gang)
Switched	Yes
Double Pole	No (Single Pole)
Twin Earth	Yes
USB Charging Output	5V DC, 2.1A
USB Output Connector	USB Type “A”
USB Standby Current	2mA
Warranty	1 Year
IP Rating	IP20
Operational Temperature	-5° to +40°C
Standards	BS 5733:2010 + A1:2014 (Ref: BS 1363-2: 1995 + A4:2012)
	BS EN 60950-1:2006 + A2:2013 (USB Charger)
	EN 61000-6-1:2007, EN 61000-6-3:2007 + A1:2011 (EMC)

Additional Information

Make certain that all USB Socket Outlets are disconnected before Mega Testing the circuit to protect electronic components

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.

Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

Errors & Omissions excluded. Specification is subject to change without notice.

V1.0

Scolmore International Ltd, 1 Scolmore Park, Landsberg, Lichfield Road Ind. Estate, Tamworth, Staffordshire, B79 7XB

Telephone: 01827 63454

E-mail: sales@scolmore.com, technical@scolmore.com

Facsimile: 01827 63362

Website: www.scolmore.com

Part M Range

DECLARATION OF CONFORMITY

1. *Issuer Name* Scolmore International Limited
2. *Issuer Address* 1 Scolmore Park, Landsberg,
Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7XB
3. *Object(s) of Declaration* Part M Range
 - a. *Group* USB Socket Outlets
 - b. *Model No.* CMA770AG, CMA771AG
4. *The object of the declaration described above is in conformity with the requirements of the following Legislations:*

Document No

2014/35/EC

Title

Low Voltage Directive

5. *All products contained within the aforementioned comply with the relevant standards and requirements listed below.*

BS 5733: 2010 + A1: 2014 (with reference to BS 1363-2: 1995 + A4: 2012)

BS EN 60950-1: 2006 + A2: 2013

EN 61000-6-1: 2007, EN 61000-6-3: 2007 + A1: 2011

6. *I hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The unit complies with all applicable Essential Requirements of the Directives.*

In conjunction with the above all manufacture and process controls are in accordance with ISO 9001:2015

Signed, for and on behalf of: Scolmore International Limited



Karl Rawlins – Senior Technical Support Engineer