



Safety Shutter Power Socket Outlets



The smooth modern lines of the MODE accessory plate will fit easily into traditional and contemporary designs alike.

All MODE 13A sockets are tested and approved to BS1363 offering assured quality and safety through our BSI Kitemark Licence KM10807.

13A UK Safety Shutter Socket Outlets

Product Range

13A UK Safety Shutter Socket Outlets

CMA1035	13A 1 Gang DP Switched Safety Shutter Socket Outlet (Twin Earth)
CMA1036	13A 2 Gang DP Switched Safety Shutter Socket Outlet (Twin Earth)
CMA1037	13A 2 Gang DP Switched Safety Shutter Socket Outlet (Twin Earth, Clean Earth)
CMA1635	13A 1 Gang DP Switched Safety Shutter Socket Outlet (Twin Earth)
CMA1835	13A 1 Gang DP Switched Safety Shutter Socket Outlet With Neon

13A UK Safety Shutter Socket Outlets (Outboard Rockers)

CMA1836	13A 2 Gang DP OB Switched Safety Shutter Socket Outlet (Twin Earth)
CMA1840	13A 2 Gang DP OB Switched Safety Shutter Socket Outlet & Neons (Twin Earth)

How To Specify

A smooth rounded profile range of white moulded wiring accessories offering antimicrobial properties to inhibit the growth of infectious diseases. Frontplate to have a maximum thickness of 9.5mm with domed head fixing screws encased with screw covers. Terminal screws to be upward facing for ease of installation. All sockets to be double pole switching with safety shutter mechanism for all 3 pin entries. Switches to be concave, marked 'ON' in grey with a minimum contact gap of 3mm and switch operation providing a decisive movement and 'click' sound.

All UK 13A socket outlets to be tested and compliant with BS1363-2 and meet an assured quality and safety system like the BSI Kitemark and covered with a 20 year manufacturer's guarantee.

13A UK Safety Shutter Socket Outlets



CMA1035, CMA1635



CMA1835



CMA1036, CMA1037



CMA1836




CMA1840


13A UK Safety Shutter Socket Outlets

Product Dimensional Drawings (mm)


CMA1035, CMA1635 & CMA1835



CMA1036 & CMA1037




CMA1836 & CMA1840




Product Wiring Diagram


CMA1035 & CMA1835




CMA1635




CMA1036



CMA1037



CMA1836 & CMA1840



Errors & Omissions excluded. Specification is subject to change without notice.

V1.0

Scolmore International Ltd, 1 Scolmore Park, Landsberg, Lichfield Road Ind. Estate, Tamworth, Staffordshire, B79 7XB

Telephone: 01827 63454

E-mail: sales@scolmore.com, technical@scolmore.com

Facsimile: 01827 63362

Website: www.scolmore.com

13A UK Safety Shutter Socket Outlets**Technical Specification****13A UK Safety Shutter Socket Outlets**

Material Composition	Front Plate, Rocker Switch & Rear Housing: Urea
	Terminals: Brass
	Terminal Screws: Steel & Yellow Passivated
	Internal Mechanism: Formed Press Brass
	Silver “on-lay” Copper / Brass Contacts
Voltage	240V~ 50Hz
Current Rating	13A
Terminal Size	5mm ø
Torque Value	2.5Nm
Cable Size	4 x 2.5mm ² , 2 x 4.0mm ²
Back Box Depth	25mm - 47mm
Double Pole Switched	Yes
Twin Earth	(1036, 1037, 1635, 1836, 1840)
Warranty	20 Years
Anti Microbial Certified	Yes
IP Rating	IP20
Operational Temperature	-5° to +40°C
Standards	KM10807 Kitemark Licence
	BS 1363-2: 2016
	Modified ISO 22196

Additional Information

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.

Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal. All white moulded accessories are manufactured using Urea Formaldehyde, which has similar inherent properties to antimicrobial additives that inhibit the growth of infectious diseases. All products were independently tested and achieved a 99.9% kill rate across all four types of the strains of bacteria - MRSA, E-Coli, Salmonella, and Klebsiella Pneumoniae.

Errors & Omissions excluded. Specification is subject to change without notice.

V1.0

Scolmore International Ltd, 1 Scolmore Park, Landsberg, Lichfield Road Ind. Estate, Tamworth, Staffordshire, B79 7XB

Telephone: 01827 63454

E-mail: sales@scolmore.com, technical@scolmore.com

Facsimile: 01827 63362

Website: www.scolmore.com



EU DECLARATION OF CONFORMITY

1. *Issuer Name* Scolmore International Limited
2. *Issuer Address* 1 Scolmore Park, Landsberg,
Lichfield Road Industrial Estate,
Tamworth, Staffordshire, B79 7XB
3. *Object(s) of Declaration* Mode Range
 - a. *Group* Safety Shutter Socket Outlets
 - b. *Model No.* CMA1035, CMA1036, CMA1037, CMA1635, CMA1835,
CMA1836 & CMA1840
4. *The object of the declaration described above is in conformity with the requirements of the following Legislations:*
5. *All products contained within the aforementioned comply with the relevant standards and requirements listed below.*

BSI Kitemark Licence KM10807
BS 1363-2: 2016

6. *I hereby declare that the equipment named above has been designed to comply with the relevant sections of the above referenced specifications. The unit complies with all applicable Essential Requirements of the Directives.*

In conjunction with the above all manufacture and process controls are in accordance with ISO 9001:2015.

This declaration has been issued under the sole responsibility of the manufacturer, signed at, for and on behalf of: Scolmore International Limited

Karl Rawlins – Senior Technical Support Engineer